



A Sierra Monitor Company

FieldServer Driver - Serial FS-8700-08 Modbus ASCII

Driver Code: MBA
Version: 1.00a

Devices Supported: Modbus ASCII devices
Interface: RS-232 or RS-485
Baud: 300 – 38400
Parity: Even, Odd, None
Data Bits: 7,8
Handshaking: RTS, RTS/CTS, None

Command/SubCommand Supported:

<u>Command</u>	<u>Description</u>
01	Read Discrete Output Status (0xxxx)
02	Read Discrete Input Status (1xxxx)
03	Read Output Registers (4xxxx)
04	Read Input Registers (3xxxx)
05	Force Single Coil (0xxxx)
06	Preset Single Register (4xxxx)
15	Force Multiple Coils (0xxxx)
16	Preset Multiple Registers (4xxxx)